

Silicon Carbide (SiC) Module - EliteSiC, 3 mohm SiC M3 MOSFET, 1200 V, 2-PACK Half Bridge Topology, F2 Package with HPS DBC

NXH003P120M3F2PTHG

The NXH003P120M3F2PTHG is a power module containing 3 m Ω / 1200 V SiC MOSFET half-bridge and a thermistor with HPS DBC in an F2 package.

Features

- 3 m Ω / 1200 V M3S SiC MOSFET Half-Bridge
- HPS DBC
- Thermistor
- Pre-Applied Thermal Interface Material (TIM)
- Press-Fit Pins
- These Devices are Pb-Free, Halide Free and are RoHS Compliant

Typical Applications

- Solar Inverter
- Uninterruptible Power Supplies
- Electric Vehicle Charging Stations
- Industrial Power





Figure 1. NXH003P120M3F2 Schematic Diagram

1

PACKAGE PICTURE



PIM36 56.7x42.5 (PRESS FIT) CASE 180BY


MARKING DIAGRAM

NXH003P120M3F2PTHG ATYYWW

NXH003P120M3F2PTHG = Specific Device Code AT = Assembly & Test Site Code

YWW = Year and Work Week

PIN CONNECTIONS



See Pin Function Description for pin names

ORDERING INFORMATION

See detailed ordering and shipping information on page 4 of this data sheet.

PIN FUNCTION DESCRIPTION

| 1 S1 Q1 Kelvin Emitter (High side switch) 2 G1 Q1 Gate (High side switch) 3 G1 Q1 Gate (High side switch) 4 S1 Q1 Kelvin Emitter (High side switch) 5 DC+ DC Positive Bus connection 6 DC+ DC Positive Bus connection 7 DC+ DC Positive Bus connection 8 DC+ DC Positive Bus connection 9 DC+ DC Positive Bus connection 10 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- <td< th=""><th>Pin</th><th>Name</th><th>Description</th></td<> | Pin | Name | Description |
|--|-----|-------|--------------------------------------|
| 3 | 1 | S1 | Q1 Kelvin Emitter (High side switch) |
| 4 S1 Q1 Kelvin Emitter (High side switch) 5 DC+ DC Positive Bus connection 6 DC+ DC Positive Bus connection 7 DC+ DC Positive Bus connection 8 DC+ DC Positive Bus connection 8 DC+ DC Positive Bus connection 9 DC+ DC Positive Bus connection 10 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 13 DC+ DC Positive Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 10 DC- DC Negative Bus connection 11 DC- DC Negative Bus connection 12 DC- DC Negative Bus connection 13 DC- DC Negative Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 1 29 TH2 Thermistor Connection 1 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge | 2 | G1 | Q1 Gate (High side switch) |
| 5 DC+ DC Positive Bus connection 7 DC+ DC Positive Bus connection 7 DC+ DC Positive Bus connection 8 DC+ DC Positive Bus connection 9 DC+ DC Positive Bus connection 10 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 13 DC+ DC Positive Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 10 DC- DC Negative Bus connection 11 DC- DC Negative Bus connection 12 DC- DC Negative Bus connection 13 DC- DC Negative Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Cate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 3 | G1 | Q1 Gate (High side switch) |
| 6 DC+ DC Positive Bus connection 7 DC+ DC Positive Bus connection 8 DC+ DC Positive Bus connection 9 DC+ DC Positive Bus connection 10 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 13 DC- DC Positive Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 1 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge | 4 | S1 | Q1 Kelvin Emitter (High side switch) |
| 7 DC+ DC Positive Bus connection 8 DC+ DC Positive Bus connection 9 DC+ DC Positive Bus connection 10 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 13 DC* DC Negative Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 31 G2 Center point of malf bridge 33 PHASE Center point of malf bridge 34 PHASE Center point of half bridge | 5 | DC+ | DC Positive Bus connection |
| 8 DC+ DC Positive Bus connection 9 DC+ DC Positive Bus connection 10 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 13 DC* DC Negative Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge | 6 | DC+ | DC Positive Bus connection |
| 9 DC+ DC Positive Bus connection 10 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 13 DC* DC Negative Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge | 7 | DC+ | DC Positive Bus connection |
| 10 DC+ DC Positive Bus connection 11 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 13 DC* DC Negative Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge | 8 | DC+ | DC Positive Bus connection |
| 11 DC+ DC Positive Bus connection 12 DC+ DC Positive Bus connection 13 DC* DC Negative Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge | 9 | DC+ | DC Positive Bus connection |
| 12 DC+ DC Positive Bus connection 13 DC* DC Negative Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge | 10 | DC+ | DC Positive Bus connection |
| 13 DC* DC Negative Bus connection 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 11 | DC+ | DC Positive Bus connection |
| 14 DC- DC Negative Bus connection 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge | 12 | DC+ | DC Positive Bus connection |
| 15 DC- DC Negative Bus connection 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 13 | DC* | DC Negative Bus connection |
| 16 DC- DC Negative Bus connection 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 14 | DC- | DC Negative Bus connection |
| 17 DC- DC Negative Bus connection 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 15 | DC- | DC Negative Bus connection |
| 18 DC- DC Negative Bus connection 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge 36 PHASE Center point of half bridge | 16 | DC- | DC Negative Bus connection |
| 19 DC- DC Negative Bus connection 20 DC- DC Negative Bus connection 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 17 | DC- | DC Negative Bus connection |
| DC- DC Negative Bus connection DC Negative Bus connection DC Negative Bus connection DC Negative Bus connection Center point of half bridge Center point of half bridge PHASE Center point of half bridge PHASE Center point of half bridge THI Thermistor Connection 1 Thermistor Connection 1 PHASE Center point of half bridge Center point of half bridge PHASE Center point of half bridge THASE Center point of half bridge Center point of half bridge PHASE Center point of half bridge | 18 | DC- | DC Negative Bus connection |
| 21 PHASE Center point of half bridge 22 PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 19 | DC- | DC Negative Bus connection |
| PHASE Center point of half bridge 23 PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 20 | DC- | DC Negative Bus connection |
| PHASE Center point of half bridge 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 21 | PHASE | Center point of half bridge |
| 24 PHASE Center point of half bridge 25 PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 22 | PHASE | Center point of half bridge |
| PHASE Center point of half bridge 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 23 | PHASE | Center point of half bridge |
| 26 S2 Q2 Kelvin Emitter (Low side switch) 27 G2 Q2 Gate (Low side switch) 28 TH1 Thermistor Connection 1 29 TH2 Thermistor Connection 2 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 24 | PHASE | Center point of half bridge |
| G2 Q2 Gate (Low side switch) Thermistor Connection 1 Thermistor Connection 2 TH2 Thermistor Connection 2 Q2 Kelvin Emitter (Low side switch) G2 Q2 Gate (Low side switch) PHASE Center point of half bridge PHASE Center point of half bridge THASE Center point of half bridge | 25 | PHASE | Center point of half bridge |
| TH1 Thermistor Connection 1 Thermistor Connection 2 Thermistor Connection 2 Q2 Kelvin Emitter (Low side switch) G2 Q2 Gate (Low side switch) PHASE Center point of half bridge PHASE Center point of half bridge PHASE Center point of half bridge TH1 Thermistor Connection 1 Thermistor Connection 2 Thermistor Conne | 26 | S2 | Q2 Kelvin Emitter (Low side switch) |
| TH2 Thermistor Connection 2 G2 Q2 Kelvin Emitter (Low side switch) G2 Q2 Gate (Low side switch) PHASE Center point of half bridge Thermistor Connection 2 Replace Switch PHASE Center point of half bridge Thermistor Connection 2 Replace Switch PHASE Center point of half bridge | 27 | G2 | Q2 Gate (Low side switch) |
| 30 S2 Q2 Kelvin Emitter (Low side switch) 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 28 | TH1 | Thermistor Connection 1 |
| 31 G2 Q2 Gate (Low side switch) 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 29 | TH2 | Thermistor Connection 2 |
| 32 PHASE Center point of half bridge 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 30 | S2 | Q2 Kelvin Emitter (Low side switch) |
| 33 PHASE Center point of half bridge 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 31 | G2 | Q2 Gate (Low side switch) |
| 34 PHASE Center point of half bridge 35 PHASE Center point of half bridge | 32 | PHASE | Center point of half bridge |
| 35 PHASE Center point of half bridge | 33 | PHASE | Center point of half bridge |
| | 34 | PHASE | Center point of half bridge |
| 36 PHASE Center point of half bridge | 35 | PHASE | Center point of half bridge |
| | 36 | PHASE | Center point of half bridge |

MAXIMUM RATINGS

| Rating | Symbol | Value | Unit |
|--|---------------------|------------|-----------|
| SIC MOSFET | | | |
| Drain-Source Voltage | V _{DSS} | 1200 | V |
| Gate-Source Voltage | V _{GS} | +22/-10 | V |
| Continuous Drain Current @ T _c = 80 °C (T _J = 175 °C) | I _D | 350 | Α |
| Pulsed Drain Current (T _J = 175 °C), (Single Pulse, R _g 2.7) | I _{Dpulse} | 870 | Α |
| Maximum Power Dissipation @ $T_C = 80 ^{\circ}C (T_J = 175 ^{\circ}C)$ | P _{tot} | 979 | W |
| Minimum Operating Junction Temperature | T _{JMIN} | -40 | °C |
| Maximum Operating Junction Temperature | T _{JMAX} | 175 | °C |
| THERMAL PROPERTIES | | | |
| Storage Temperature Range | T _{stg} | -40 to 150 | °C |
| TIM Layer Thickness | T _{TIM} | 160 ±20 | μm |
| INSULATION PROPERTIES | | | |
| Isolation Test Voltage, t = 1 s, 60 Hz | V _{is} | 4800 | V_{RMS} |
| Creepage Distance | | 12.7 | mm |
| СТІ | | 600 | |
| Substrate Ceramic Material | | HPS | |
| Substrate Ceramic Material Thickness | | 0.38 | mm |
| Substrate Warpage (Note 2) | W | Max 0.18 | mm |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

- 1. Refer to ELECTRICAL CHĂRACTERISTICS, RECOMMENDED OPERATING RANGES and/or APPLICATION INFORMATION for Safe Operating parameters.
- 2. Height difference between horizontal plane and substrate copper bottom.
- 3. Package has limited continues drain current due to pressfit pin current capability 30 A per pin.

RECOMMENDED OPERATING RANGES

| Rating | Symbol | Min | Max | Unit |
|---------------------------------------|--------|-----|-----|------|
| Module Operating Junction Temperature | T_J | -40 | 150 | °C |

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

ELECTRICAL CHARACTERISTICS (T_J = 25 °C unless otherwise noted)

| Parameter | Symbol | Test Conditions | Min | Тур | Max | Unit |
|---------------------------------|---------------------|---|------|--------|-----|------|
| SIC MOSFET CHARACTERISTICS | | | | | | |
| Zero Gate Voltage Drain Current | I _{DSS} | V _{GS} = 0 V, V _{DS} = 1200 V | _ | _ | 300 | μΑ |
| Drain-Source On Resistance | R _{DS(ON)} | $V_{GS} = 18 \text{ V}, I_D = 200 \text{ A}, T_J = 25 ^{\circ}\text{C}$ | _ | 3.19 | 5 | mΩ |
| | | V_{GS} = 18 V, I_{D} = 200 A, T_{J} = 125 °C | _ | 5.25 | _ | |
| | | V_{GS} = 18 V, I_{D} = 200 A, T_{J} = 150 °C | _ | 5.88 | _ | |
| Gate-Source Threshold Voltage | V _{GS(TH)} | $V_{GS} = V_{DS}$, $I_D = 160 \text{ mA}$ | 1.8 | 2.4 | 4.4 | V |
| Gate Leakage Current | I _{GSS} | $V_{GS} = -10 \text{ V} / 20 \text{ V}, V_{DS} = 0 \text{ V}$ | -800 | - | 800 | nA |
| Gate-Resistance | R_{G} | f = 1 MHz | _ | 0.1875 | _ | Ω |
| Input Capacitance | C _{ISS} | $V_{DS} = 800 \text{ V}, V_{GS} = 0 \text{ V}, f = 100 \text{ kHz}$ | _ | 20889 | _ | pF |
| Reverse Transfer Capacitance | C _{RSS} |] | _ | 90 | - | |
| Output Capacitance | C _{OSS} | | - | 1225 | - | |

ELECTRICAL CHARACTERISTICS (T_J = 25 °C unless otherwise noted) (continued)

| Parameter | Symbol | Test Conditions | Min | Тур | Max | Unit |
|---------------------------------------|-----------------------|---|-----|-------|-----|------|
| SIC MOSFET CHARACTERISTICS | • | | | • | | |
| Total Gate Charge | Q _{G(TOTAL)} | $V_{DS} = 800 \text{ V}, V_{GS} = -5/20 \text{ V},$ | - | 1195 | - | nC |
| Gate-Source Charge | Q _{GS} | I _D = 200 A | - | 232 | - | nC |
| Gate-Drain Charge | Q _{GD} | 1 | _ | 210 | _ | nC |
| Turn-on Delay Time | t _{d(on)} | T _J = 25 °C | - | 49 | - | ns |
| Rise Time | t _r | $V_{DS} = 600 \text{ V}, I_D = 200 \text{ A}$ $V_{GS} = -5 \text{ V} / 18 \text{ V}, R_G = 1 \Omega$ | - | 17 | - | 1 |
| Turn-off Delay Time | t _{d(off)} | | - | 144 | - | 1 |
| Fall Time | t _f | | - | 16 | - | 1 |
| Turn-on Switching Loss per Pulse | E _{ON} | | - | 1.79 | - | mJ |
| Turn-off Switching Loss per Pulse | E _{OFF} | | - | 1.13 | - | 1 |
| Turn-on Delay Time | t _{d(on)} | T _J = 150 °C | - | 48 | - | ns |
| Rise Time | t _r | $V_{DS} = 600 \text{ V}, I_D = 200 \text{ A}$ $V_{GS} = -5 \text{ V} / 18 \text{ V}, R_G = 1 \Omega$ | _ | 15 | - | |
| Turn-off Delay Time | t _{d(off)} | | _ | 154 | - | |
| Fall Time | t _f | | _ | 15 | - | |
| Turn-on Switching Loss per Pulse | E _{ON} | | _ | 1.94 | - | mJ |
| Turn-off Switching Loss per Pulse | E _{OFF} | | _ | 1.12 | - | |
| Diode Forward Voltage | V_{SD} | I _D = 200 A, T _J = 25 °C | - | 4.8 | 7.5 | V |
| | | I _D = 200 A, T _J = 125 °C | - | 4.5 | - | |
| | | I _D = 200 A, T _J = 150 °C | - | 4.4 | - | |
| Thermal Resistance – Chip-to-Case | R _{thJC} | M1, M2 | - | 0.097 | - | °C/W |
| Thermal Resistance – Chip-to-Heatsink | R _{thJH} | Thermal grease, Thickness = 2 Mil +2%, A = 2.8 W/mK | - | 0.202 | - | °C/W |
| THERMISTOR CHARACTERISTICS | • | | | | | |
| Nominal Resistance | R ₂₅ | T _{NTC} = 25 °C | - | 5 | - | kΩ |
| | R ₁₀₀ | T _{NTC} = 100 °C | - | 493 | - | Ω |
| | R ₁₅₀ | T _{NTC} = 150 °C | - | 159.5 | - | Ω |
| Deviation of R ₁₀₀ | ΔR/R | T _{NTC} = 100 °C | -5 | - | 5 | % |
| Power Dissipation - Recommended Limit | P _D | 0.15 mA, Non-self-heating Effect | - | 0.1 | - | mW |
| Power Dissipation – Absolute Maximum | P _D | 5 mA | - | 34.2 | - | mW |
| Power Dissipation Constant | | | - | 1.4 | - | mW/K |
| B-value | | B (25/50), Tolerance ±2% | - | 3375 | - | K |
| B-value | | B (25/100), Tolerance ±2% | _ | 3436 | _ | K |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

ORDERING INFORMATION

| Orderable Part Number | Marking | Package | Shipping |
|-----------------------|--------------------|---|-------------------------|
| NXH003P120M3F2PTHG | NXH003P120M3F2PTHG | F2HALFBR: Case 180BY Press-fit Pins with pre-applied thermal interface material (TIM) (Pb-Free / Halide Free) | 20 Units / Blister Tray |

TYPICAL CHARACTERISTIC

(M1/M2 SiC MOSFET CHARACTERISTIC)




Figure 2. MOSFET Typical Output Characteristic




Figure 4. MOSFET Typical Transfer Characteristic




Figure 3. MOSFET Typical Output Characteristic




Figure 5. Body Diode Forward Characteristic

TYPICAL CHARACTERISTIC

(M1/M2 SiC MOSFET CHARACTERISTIC)




Figure 6. Gate-to-Source Voltage vs. Total Charge




Figure 7. Capacitance vs. Drain-to-Source Voltage

TYPICAL CHARACTERISTIC




Figure 8. Typical Switching Loss Eon vs. ID




Figure 10. Typical Switching Loss E_{off} vs. I_{D}




Figure 9. Typical Switching Loss E_{on} vs. R_{G}




Figure 11. Typical Switching Loss E_{off} vs. R_{G}




Figure 13. E_{rr} vs. R_G

TYPICAL CHARACTERISTIC




Figure 14. Typical Switching Loss T_{don} vs. I_D




Figure 16. Typical Switching Loss T_{doff} vs. I_D




Figure 18. Typical Switching Loss T_r vs. I_D




Figure 15. Typical Switching Loss T_{don} vs. R_G




Figure 17. Typical Switching Loss T_{doff} vs. R_{G}




Figure 19. Typical Switching Loss T_r vs. R_G

TYPICAL CHARACTERISTIC




Figure 20. Typical Switching Loss T_{f} vs. I_{D}




Figure 22. di/dt ON vs. I_D




Figure 24. di/dt OFF vs. I_D




Figure 21. Typical Switching Loss T_f vs. R_G




Figure 23. di/dt ON vs. R_G




Figure 25. di/dt OFF vs. R_G

TYPICAL CHARACTERISTIC




Figure 26. dv/dt ON vs. I_{D}




Figure 27. dv/dt ON vs. R_G




Figure 28. dv/dt OFF vs. I_{D}




Figure 29. dv/dt OFF vs. R_G




Figure 30. RBSOA I_D vs. V_{DS}

TYPICAL CHARACTERISTIC

(M1/M1 SiC MOSFET CHARACTERISTIC)




Figure 31. MOSFET Junction-to-Case Transient Thermal Impedance

Table 1. FOSTER NETWORKS - M1, M2

| | M1 | | M | 12 |
|------------------|-------------|-------------|-------------|-------------|
| Foster Element # | Rth (K/W) | Cth (Ws/K) | Rth (K/W) | Cth (Ws/K) |
| 1 | 0.002119710 | 0.006269327 | 0.002085717 | 0.005919216 |
| 2 | 0.002237509 | 0.044417021 | 0.002262963 | 0.041549892 |
| 3 | 0.010754082 | 0.080568359 | 0.011217723 | 0.075947544 |
| 4 | 0.012973790 | 0.473570059 | 0.013624461 | 0.468022154 |
| 5 | 0.071830979 | 0.438172158 | 0.07157749 | 0.444577769 |

Table 2. CAUER NETWORKS - M1, M2

| | M1 | | N | 12 |
|-----------------|-------------|-------------|-------------|-------------|
| Cauer Element # | Rth (K/W) | Cth (Ws/K) | Rth (K/W) | Cth (Ws/K) |
| 1 | 0.003228661 | 0.005029516 | 0.003176874 | 0.004749202 |
| 2 | 0.005914795 | 0.025033712 | 0.005878559 | 0.023599253 |
| 3 | 0.015486364 | 0.043255417 | 0.015761478 | 0.041433746 |
| 4 | 0.041123543 | 0.201827107 | 0.04214085 | 0.20355778 |
| 5 | 0.034162706 | 0.484541759 | 0.033810593 | 0.506186577 |

REVISION HISTORY

| Revision | Description of Changes | Date |
|----------|--|------------|
| 4 | Added package current limitation note, updated RBSOA characteristic, updated Id pulse value. | 11/03/2025 |

This document has undergone updates prior to the inclusion of this revision history table. The changes tracked here only reflect updates made on the noted approval dates.



PIM36 56.70x42.50x12.00 CASE 180BY ISSUE E **DATE 20 DEC 2023** NOTES: 1. CONTROLLING DIMENSION: MILLIMETERS 2. PIN POSITION TOLERANCE IS ± 0.4mm PACKAGE MARKING LOCATION 3. PRESS FIT PIN MILLIMETERS NOM. MAX. DIM MIN. 11.65 12.35 12.00 Α1 16.10 16.50 16.90 A2 0.00 0.35 0.60 Ė2 А3 13.35 12.95 13.75 1.15 1.25 b 1.20 b1 0.59 0.64 0.69 D 56.40 56.70 57.00 D1 4.40 4.50 4.60 D2 50.85 51.00 51.15 47.70 48.00 48.30 42.35 42.50 E1 42.65 ØΡ E2 52.90 53.00 53.10 **E**3 62.30 62.80 63.30 SIDE VIEW TOP VIEW E4 4.90 5.00 5.10 Р 2.20 2.30 2.40 25.5 24.0 24.0 20.8 20.8 11.2 **END VIEW** DBC EXPOSAL **GENERIC MARKING DIAGRAM* ATYYWW** Ø0.94~1.09 PLATED THRU HOLE FRONTSIDE MARKING 2D RECOMMENDED CODE **MOUNTING PATTERN**

| DOCUMENT NUMBER: | 98AON19725H | Electronic versions are uncontrolled except when accessed directly from Printed versions are uncontrolled except when stamped "CONTROLLED | |
|------------------|-------------------------|--|-------------|
| DESCRIPTION: | PIM36 56.70x42.50x12.00 | | PAGE 1 OF 1 |

may not follow the Generic Marking.

*This information is generic. Please refer to device data

sheet for actual part marking. Pb-Free indicator, "G" or

microdot " • ", may or may not be present. Some products

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

BACKSIDE MARKING

YYWW = Year and Work Week Code

= Assembly & Test Site Code

XXXXX = Specific Device Code

onsemi, Onsemi, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales