

# 2.5 V / 3.3 V Differential 2 X 2 Crosspoint Switch with LVPECL Outputs

Multi-Level Inputs w/ Internal Termination

## NB6L72

### Description

The NB6L72 is a clock or data high-bandwidth fully differential 2 x 2 Crosspoint Switch with internal source termination and LVPECL output structure, optimized for low skew and minimal jitter. The differential inputs incorporate internal 50  $\Omega$  termination resistors and will accept LVPECL, CML, LVDS, LVCMOS, or LVTTTL logic levels. The SELECT inputs are single-ended and can be driven with LVCMOS/LVTTTL.

The differential LVPECL outputs provide 800 mV output swings when externally terminated with a 50  $\Omega$  resistor to  $V_{CC} - 2.0$  V.


The device is offered in a small 3 mm x 3 mm 16-pin QFN package.

The NB6L72 is a member of the ECLinPS MAX<sup>™</sup> family of high performance clock and data management products.

### Features

- Input Clock Frequency > 3.0GHz
- Input Data Rate > 3 Gb/s
- 425 ps Typical Propagation Delay
- 100 ps Typical Rise and Fall Times
- 0.5 ps maximum RMS Clock Jitter
- LVPECL, CML or LVDS Input Compatible
- Differential LVPECL Outputs, 800 mV Amplitude, Typical
- Operating Range:  $V_{CC} = 2.375$  V to 3.63 V with GND = 0 V
- Internal 50  $\Omega$  Input Termination Provided
- Functionally Compatible with Existing 2.5 V/3.3 V LVEL, LVEP, EP, and SG Devices
- -40°C to +85°C Ambient Operating Temperature
- These are Pb-Free Devices

### MARKING DIAGRAM\*



A = Assembly Location  
L = Wafer Lot  
Y = Year  
W = Work Week  
▪ = Pb-Free Package  
(Note: Microdot may be in either location)

\*For additional marking information, refer to Application Note AND8002/D.

### ORDERING INFORMATION

See detailed ordering and shipping information in the package dimensions section on page 10 of this data sheet.

# NB6L72





Figure 1. Logic/Block Diagram

## NB6L72



**Table 1. INPUT/OUTPUT SELECT TRUTH TABLE**

| SEL0* | SEL1* | Q0 | Q1 |
|-------|-------|----|----|
| L     | L     | D0 | D0 |
| H     | L     | D1 | D0 |
| L     | H     | D0 | D1 |
| H     | H     | D1 | D1 |

\*Defaults HIGH when left open

**Figure 2. Pin Configuration (Top View)**

**Table 2. PIN DESCRIPTION**

| Pin | Name            | I/O                                      | Description                                                                                                                                                                                                                                                                                                                        |
|-----|-----------------|------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1   | SEL0            | LVTTTL, LVCMOS Input                     | Select Logic Input control that selects D0 or D1 to output Q0. See Table 1, Select Input Function Table. Pin defaults HIGH when left open                                                                                                                                                                                          |
| 2   | D0              | LVPECL, CML, LVDS, LVTTTL, LVCMOS, Input | Noninverted Differential Input. Note 1.                                                                                                                                                                                                                                                                                            |
| 3   | $\overline{D0}$ | LVPECL, CML, LVDS, LVTTTL, LVCMOS, Input | Inverted Differential Input. Note 1.                                                                                                                                                                                                                                                                                               |
| 4   | VTD0            | –                                        | Internal 50 $\Omega$ Termination Pin. Note 1.                                                                                                                                                                                                                                                                                      |
| 5   | VTD1            | –                                        | Internal 50 $\Omega$ termination pin. Note 1.                                                                                                                                                                                                                                                                                      |
| 6   | D1              | LVPECL, CML, LVDS, LVTTTL, LVCMOS, Input | Noninverted Differential Input. Note 1.                                                                                                                                                                                                                                                                                            |
| 7   | $\overline{D1}$ | LVPECL, CML, LVDS, LVTTTL, LVCMOS, Input | Inverted Differential Input. Note 1.                                                                                                                                                                                                                                                                                               |
| 8   | SEL1            | LVTTTL, LVCMOS Input                     | Select Logic Input control that selects D0 or D1 to output Q1. See Table 1, Select Input Function Table. Pin defaults HIGH when left open                                                                                                                                                                                          |
| 9   | GND             | –                                        | Negative Supply Voltage                                                                                                                                                                                                                                                                                                            |
| 10  | $\overline{Q1}$ | LVPECL Output                            | Inverted Differential Output. Typically Terminated with 50 $\Omega$ Resistor to $V_{CC} - 2.0$ V.                                                                                                                                                                                                                                  |
| 11  | Q1              | LVPECL Output                            | Noninverted Differential Output. Typically Terminated with 50 $\Omega$ Resistor to $V_{CC} - 2.0$ V.                                                                                                                                                                                                                               |
| 12  | $V_{CC}$        | –                                        | Positive Supply Voltage                                                                                                                                                                                                                                                                                                            |
| 13  | $V_{CC}$        | –                                        | Positive Supply Voltage                                                                                                                                                                                                                                                                                                            |
| 14  | $\overline{Q0}$ | LVPECL Output                            | Inverted Differential Reset Input. Typically Terminated with 50 $\Omega$ Resistor to $V_{CC} - 2.0$ V.                                                                                                                                                                                                                             |
| 15  | Q0              | LVPECL Output                            | Noninverted Differential Reset Input. Typically Terminated with 50 $\Omega$ Resistor to $V_{CC} - 2.0$ V.                                                                                                                                                                                                                          |
| 16  | GND             | –                                        | Negative Supply Voltage                                                                                                                                                                                                                                                                                                            |
| –   | EP              | –                                        | The Exposed Pad (EP) on the QFN-16 package bottom is thermally connected to the die for improved heat transfer out of package. The exposed pad must be attached to a heat-sinking conduit. The pad is not electrically connected to the die, but is recommended to be electrically and thermally connected to GND on the PC board. |

1. In the differential configuration when the input termination pin (VTDn,  $\overline{VTDn}$ ) are connected to a common termination voltage or left open, and if no signal is applied on Dn/ $\overline{Dn}$  input, then the device will be susceptible to self-oscillation.
2. All  $V_{CC}$  and GND pins must be externally connected to a power supply for proper operation.

**Table 3. ATTRIBUTES**

| Characteristics                                        | Value                |
|--------------------------------------------------------|----------------------|
| ESD Protection Human Body Model<br>Machine Model       | > 2 kV<br>> 200 V    |
| Moisture Sensitivity 16-QFN                            | Level 1              |
| Flammability Rating Oxygen Index: 28 to 34             | UL 94 V-0 @ 0.125 in |
| Transistor Count                                       |                      |
| Meets or exceeds JEDEC Spec EIA/JESD78 IC Latchup Test |                      |

For additional information, see Application Note AND8003/D.

**Table 4. MAXIMUM RATINGS**

| Symbol            | Parameter                                                   | Condition 1         | Condition 2                          | Rating                | Unit         |
|-------------------|-------------------------------------------------------------|---------------------|--------------------------------------|-----------------------|--------------|
| V <sub>CC</sub>   | Positive Power Supply                                       | GND = 0 V           |                                      | 4.0                   | V            |
| V <sub>IO</sub>   | Positive Input/Output Voltage                               | GND = 0 V           | $-0.5 \leq V_{IO} \leq V_{CC} + 0.5$ | 4.5                   | V            |
| V <sub>INPP</sub> | Differential Input Voltage  D – $\overline{D}$              |                     |                                      | V <sub>CC</sub> – GND | V            |
| I <sub>IN</sub>   | Input Current Through R <sub>T</sub> (50 $\Omega$ Resistor) | Static<br>Surge     |                                      | 45<br>80              | mA<br>mA     |
| I <sub>OUT</sub>  | Output Current (LVPECL Output)                              | Continuous<br>Surge |                                      | 50<br>100             | mA<br>mA     |
| T <sub>A</sub>    | Operating Temperature Range                                 | QFN-16              |                                      | –40 to +85            | °C           |
| T <sub>stg</sub>  | Storage Temperature Range                                   |                     |                                      | –65 to +150           | °C           |
| $\theta_{JA}$     | Thermal Resistance (Junction-to-Ambient) (Note 3)           | 0 lfpm<br>500 lfpm  | QFN-16<br>QFN-16                     | 42<br>35              | °C/W<br>°C/W |
| $\theta_{JC}$     | Thermal Resistance (Junction-to-Case)                       | (Note 3)            | QFN-16                               | 4                     | °C/W         |
| T <sub>sol</sub>  | Wave Solder Pb-Free                                         |                     |                                      | 265                   | °C           |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

3. JEDEC standard multilayer board – 2S2P (2 signal, 2 power) with 8 filled thermal vias under exposed pad.

## NB6L72

**Table 5. DC CHARACTERISTICS, Multi-Level Inputs**  $V_{CC} = 2.375\text{ V to }3.63\text{ V}$ ,  $GND = 0\text{ V}$ ,  $T_A = -40^{\circ}\text{C to }+85^{\circ}\text{C}$

| Symbol | Characteristic | Min | Typ | Max | Unit |
|--------|----------------|-----|-----|-----|------|
|--------|----------------|-----|-----|-----|------|

### POWER SUPPLY CURRENT

|          |                                                |    |    |    |    |
|----------|------------------------------------------------|----|----|----|----|
| $I_{CC}$ | Power Supply Current (Inputs and Outputs Open) | 40 | 60 | 80 | mA |
|----------|------------------------------------------------|----|----|----|----|

### LVPECL OUTPUTS (Notes 4 and 5)

|          |                                                                           |                                 |                                |                                |    |
|----------|---------------------------------------------------------------------------|---------------------------------|--------------------------------|--------------------------------|----|
| $V_{OH}$ | Output HIGH Voltage<br>$V_{CC} = 3.3\text{ V}$<br>$V_{CC} = 2.5\text{ V}$ | $V_{CC} - 1075$<br>2225<br>1425 | $V_{CC} - 950$<br>2350<br>1550 | $V_{CC} - 825$<br>2475<br>1675 | mV |
| $V_{OL}$ | Output LOW Voltage<br>$V_{CC} = 3.3\text{ V}$<br>$V_{CC} = 2.5\text{ V}$  | $V_{CC} - 1825$<br>1475<br>675  | $V_{CC} - 1725$<br>1575<br>775 | $V_{CC} - 1625$<br>1675<br>875 | mV |

### DIFFERENTIAL INPUT DRIVEN SINGLE-ENDED (see Figures 4 and 5) (Note 6)

|           |                                                            |                |  |                |    |
|-----------|------------------------------------------------------------|----------------|--|----------------|----|
| $V_{th}$  | Input Threshold Reference Voltage Range (Note 7)           | 1125           |  | $V_{CC} - 150$ | mV |
| $V_{IH}$  | Single-ended Input HIGH Voltage                            | $V_{th} + 150$ |  | $V_{CC}$       | mV |
| $V_{IL}$  | Single-ended Input LOW Voltage                             | GND            |  | $V_{th} - 150$ | mV |
| $V_{ISE}$ | Single-ended Input Voltage Amplitude ( $V_{IH} - V_{IL}$ ) | 300            |  | $V_{CC} - GND$ | mV |

### DIFFERENTIAL INPUTS DRIVEN DIFFERENTIALLY (see Figures 7 and 9)

|           |                                                                                |      |  |                |               |
|-----------|--------------------------------------------------------------------------------|------|--|----------------|---------------|
| $V_{IHD}$ | Differential Input HIGH Voltage                                                | 1050 |  | $V_{CC}$       | mV            |
| $V_{ILD}$ | Differential Input LOW Voltage                                                 | GND  |  | $V_{CC} - 150$ | mV            |
| $V_{ID}$  | Differential Input Voltage ( $D_n, \overline{D_n}$ ) ( $V_{IHD} - V_{ILD}$ )   | 150  |  | $V_{CC} - GND$ | mV            |
| $V_{CMR}$ | Input Common Mode Range (Differential Configuration) (Note 9)                  | 950  |  | $V_{CC} - 75$  | mV            |
| $I_{IH}$  | Input HIGH Current $D_n/\overline{D_n}$ , ( $V_{TDn}/\overline{V_{TDn}}$ Open) | -150 |  | +150           | $\mu\text{A}$ |
| $I_{IL}$  | Input LOW Current $D_n/\overline{D_n}$ , ( $V_{TDn}/\overline{V_{TDn}}$ Open)  | -150 |  | +150           | $\mu\text{A}$ |

### SINGLE-ENDED LVCMOS/LVTTL CONTROL INPUTS

|          |                                 |      |  |          |               |
|----------|---------------------------------|------|--|----------|---------------|
| $V_{IH}$ | Single-ended Input HIGH Voltage | 2000 |  | $V_{CC}$ | mV            |
| $V_{IL}$ | Single-ended Input LOW Voltage  | GND  |  | 800      | mV            |
| $I_{IH}$ | Input HIGH Current              | -10  |  | 10       | $\mu\text{A}$ |
| $I_{IL}$ | Input LOW Current               | -150 |  | 0        | $\mu\text{A}$ |

### TERMINATION RESISTORS

|           |                                     |    |    |    |          |
|-----------|-------------------------------------|----|----|----|----------|
| $R_{TIN}$ | Internal Input Termination Resistor | 40 | 50 | 60 | $\Omega$ |
|-----------|-------------------------------------|----|----|----|----------|

NOTE: Device will meet the specifications after thermal equilibrium has been established when mounted in a test socket or printed circuit board with maintained transverse airflow greater than 500 lfm.

4. LVPECL outputs loaded with  $50\ \Omega$  to  $V_{CC} - 2.0\text{ V}$  for proper operation.
5. Input and output parameters vary 1:1 with  $V_{CC}$ .
6.  $V_{th}$ ,  $V_{IH}$ ,  $V_{IL}$ , and  $V_{ISE}$  parameters must be complied with simultaneously.
7.  $V_{th}$  is applied to the complementary input when operating in single-ended mode.
8.  $V_{IHD}$ ,  $V_{ILD}$ ,  $V_{ID}$  and  $V_{CMR}$  parameters must be complied with simultaneously.
9.  $V_{CMR}$  minimum varies 1:1 with GND,  $V_{CMR}$  max varies 1:1 with  $V_{CC}$ . The  $V_{CMR}$  range is referenced to the most positive side of the differential input signal.

## NB6L72

**Table 6. AC CHARACTERISTICS**  $V_{CC} = 2.375\text{ V to }3.63\text{ V}$ ,  $V_{EE} = 0\text{ V}$ , or  $V_{CC} = 0\text{ V}$ ,  $V_{EE} = -2.375\text{ V to }-3.63\text{ V}$ ,  
 $T_A = -40^\circ\text{C to }+85^\circ\text{C}$ ; (Note 10)

| Symbol                   | Characteristic                                                                                                                                                                       | Min               | Typ                    | Max            | Unit |
|--------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------|------------------------|----------------|------|
| $V_{OUTPP}$              | Output Voltage Amplitude (@ $V_{INPPmin}$ )<br>(Note 14) (See Figure 16)<br>$f_{in} \leq 1.5\text{ GHz}$<br>$f_{in} \leq 2.5\text{ GHz}$<br>$f_{in} \leq 3.0\text{ GHz}$             | 520<br>380<br>320 | 800<br>650<br>500      |                | mV   |
| $t_{PLH}$ ,<br>$t_{PHL}$ | Propagation Delay (@0.5GHz)<br>Dn to Qn<br>SELn to Qn                                                                                                                                | 325               | 425                    | 525            | ps   |
| $t_{SKEW}$               | Duty Cycle Skew (Note 11)<br>Within Device Skew<br>Device to Device Skew (Note 12)                                                                                                   |                   | 5                      | 20<br>20<br>80 | ps   |
| $t_{DC}$                 | Output Clock Duty Cycle<br>(Reference Duty Cycle = 50%)<br>$f_{in} \leq 3.0\text{ GHz}$                                                                                              | 40                | 50                     | 60             | %    |
| $t_{JITTER}$             | RMS Random Clock Jitter (Note 13)<br>Data Dependent Jitter<br>$f_{in} = 2.5\text{ GHz}$<br>$f_{in} = 3.0\text{ GHz}$<br>$f_{DATA} = 2.5\text{ Gb/s}$<br>$f_{DATA} = 3.0\text{ Gb/s}$ |                   | 0.2<br>0.3<br>12<br>15 | 0.5<br>1       | ps   |
| $V_{INPP}$               | Input Voltage Swing/Sensitivity<br>(Differential Configuration) (Note 14)                                                                                                            | 150               |                        | $V_{CC} - GND$ | mV   |
| $t_r, t_f$               | Output Rise/Fall Times @ 0.5 GHz (20% – 80%)<br>Q, $\bar{Q}$                                                                                                                         |                   | 100                    | 160            | ps   |

NOTE: Device will meet the specifications after thermal equilibrium has been established when mounted in a test socket or printed circuit board with maintained transverse airflow greater than 500 lfm.

10. Measured by forcing  $V_{INPP}$  (minimum) from a 50% duty cycle clock source. All loading with an external  $R_L = 50\ \Omega$  to  $V_{CC} - 2.0\text{ V}$ . Input edge rates 40 ps (20% – 80%).

11. Duty cycle skew is measured between differential outputs using the deviations of the sum of  $T_{pw-}$  and  $T_{pw+}$  @ 0.5 GHz.

12. Device to device skew is measured between outputs under identical transition @ 0.5 GHz.

13. Additive RMS jitter with 50% duty cycle clock signal.

14. Input and output voltage swing is a single-ended measurement operating in differential mode.

# NB6L72




Figure 3. Input Structure




Figure 4. Differential Input Driven Single-Ended




Figure 5.  $V_{th}$  Diagram




Figure 6. Differential Inputs Driven Differentially




Figure 7. Differential Inputs Driven Differentially




Figure 8.  $V_{CMR}$  Diagram




Figure 9. AC Reference Measurement

## NB6L72




Figure 10. LVPECL Interface




Figure 11. LVDS Interface




Figure 12. Standard 50  $\Omega$  Load CML Interface




Figure 13. Capacitor-Coupled  
Differential Interface  
(VT Connected to  $V_{REFAC}$ )





Figure 14. Capacitor-Coupled  
Single-Ended Interface  
(VT Connected to  $V_{REFAC}$ )


\* $V_{REFAC}$  bypassed to ground with a 0.01  $\mu$ F capacitor




## NB6L72



**Figure 15. Typical Termination for Output Driver and Device Evaluation**  
(See Application Note AND8020/D – Termination of ECL Logic Devices.)




**Figure 16. Output Voltage Amplitude ( $V_{OUTPP}$ ) versus Output Frequency at Ambient Temperature (Typical)**



**Figure 17. Typical Output Wave Form – Data Signal PRBS  $2^{23}-1$  Room Temperature, 400 mV Input Amplitude,  $V_{CC} = 2.5 \text{ V}$ , 2.488 Gb/s (X-scale = 80 ps/DIV; y-Scale = 100 mV/DIV)**

## NB6L72



Total Jitter = 28 ps  
Device Jitter = 15 ps  
Input Jitter = 13 ps

Figure 18. Typical Output Wave Form – Data Signal PRBS 2<sup>23</sup>-1 Room Temperature, 75 mV Input Amplitude, 3 Gb/s (X-scale = 80 ps/DIV; y-Scale = 100 mV/DIV)

### ORDERING INFORMATION

| Device      | Package             | Shipping <sup>†</sup> |
|-------------|---------------------|-----------------------|
| NB6L72MNG   | QFN-16<br>(Pb-free) | 123 Units / Rail      |
| NB6L72MNR2G | QFN-16<br>(Pb-free) | 3000 / Tape & Reel    |

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.




# MECHANICAL CASE OUTLINE PACKAGE DIMENSIONS



SCALE 2:1


## QFN16 3x3, 0.5P CASE 485G ISSUE G

DATE 08 OCT 2021




### NOTES:

1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
2. CONTROLLING DIMENSION: MILLIMETERS
3. DIMENSION b APPLIES TO PLATED TERMINAL AND IS MEASURED BETWEEN 0.15 AND 0.30 MM FROM THE TERMINAL TIP.
4. COPLANARITY APPLIES TO THE EXPOSED PAD AS WELL AS THE TERMINALS.




DETAIL B  
ALTERNATE  
CONSTRUCTIONS




DETAIL A  
ALTERNATE TERMINAL  
CONSTRUCTIONS

| DIM | MILLIMETERS |      |      |
|-----|-------------|------|------|
|     | MIN.        | NDM. | MAX. |
| A   | 0.80        | 0.90 | 1.00 |
| A1  | 0.00        | 0.03 | 0.05 |
| A3  | 0.20 REF    |      |      |
| b   | 0.18        | 0.24 | 0.30 |
| D   | 3.00 BSC    |      |      |
| D2  | 1.65        | 1.75 | 1.85 |
| E   | 3.00 BSC    |      |      |
| E2  | 1.65        | 1.75 | 1.85 |
| e   | 0.50 BSC    |      |      |
| k   | 0.18 TYP    |      |      |
| L   | 0.30        | 0.40 | 0.50 |
| L1  | 0.00        | 0.08 | 0.15 |

### MOUNTING FOOTPRINT



### GENERIC MARKING DIAGRAM\*



XXXXX = Specific Device Code  
A = Assembly Location  
L = Wafer Lot  
Y = Year  
W = Work Week  
▪ = Pb-Free Package

(Note: Microdot may be in either location)

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "▪", may or may not be present. Some products may not follow the Generic Marking.

|                  |                 |                                                                                                                                                                                     |
|------------------|-----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| DOCUMENT NUMBER: | 98AON04795D     | Electronic versions are uncontrolled except when accessed directly from the Document Repository.<br>Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |
| DESCRIPTION:     | QFN16 3X3, 0.5P | PAGE 1 OF 1                                                                                                                                                                         |

onsemi and onsemi are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

**onsemi**, **Onsemi**, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## ADDITIONAL INFORMATION

### TECHNICAL PUBLICATIONS:

Technical Library: [www.onsemi.com/design/resources/technical-documentation](http://www.onsemi.com/design/resources/technical-documentation)  
onsemi Website: [www.onsemi.com](http://www.onsemi.com)

### ONLINE SUPPORT: [www.onsemi.com/support](http://www.onsemi.com/support)

For additional information, please contact your local Sales Representative at  
[www.onsemi.com/support/sales](http://www.onsemi.com/support/sales)