

ON Semiconductor

Is Now

onsemi™

To learn more about onsemi™, please visit our website at
www.onsemi.com

onsemi and **onsemi** and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi** product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner. Other names and brands may be claimed as the property of others.

AX5043 Sending FM Tones (ZVEI)

Introduction

This application note describes how to use the AX5043 for transmitting FM tones as they are used for selective calling (ZVEI and similar schemes).

The AX5043_TX_FM_tones_(ZVEI) Project

The MASTER/main.c file of the AX5043_TX_FM_tones_(ZVEI) project demonstrates the transmission of FM tones. Upon pushing button “D” on the DVK-2 mainboard the tones encoding the digits ‘A’, ‘5’, ‘0’, ‘4’, ‘3’ in the ZVEI scheme are transmitted.

The carrier frequency is 868.3 MHz, ± 3 kHz FM deviation are used and an 48 MHz TCXO is assumed.

The FM tones are generated as follows: The AX5043 is set up transmitting CW. Using a TIMER0 interrupt the frequency register is updated periodically in order to generate the desired tone. This is done for a defined number of sampling points. The procedure can be repeated for generating further tones. Finally the AX5043 is put into power-down mode and the MCU goes into sleep mode.

Note: This project was derived from an AX-RadioLAB project. However, due to the nature of the task, the dependence of the AXRadioV2API has been removed and communication with the AX5043 radio chip is done directly in the code or via LibMF routines. In order to work with this project MASTER/MASTER.cbp should be opened using the AXCode::Blocks IDE.

The files axradiolabstate.xml and AX_Radio_Lab_output/* have been kept. Thus it is still possible to open the project using AX-RadioLAB in order to compute register values when attempting to change parameters. However, the files AX_Radio_Lab_output/* are not used by the code. Changed register values have to be copied manually from AX_Radio_Lab_output/config.c into the init_ax5043() in main.c (see below).

When using the F143-MINI-DVK rather than the DVK-2 it is necessary to comment in the line “`///define MINI_KIT” and to comment out “#define USE_LCD” at the top of main.c`

Routines

`void init_ax5043(void)`

This routine resets the AX5043, configures the registers necessary for transmit and ranges the PLL for the frequency configured in the FREQA register. In order to change parameters as the carrier frequency, internal vs external VCO, XTAL or TCXO frequency etc. It is easiest to open the



ON Semiconductor®

www.onsemi.com

APPLICATION NOTE

project with with AX-RadioLAB, change the corresponding parameters and update the register values in `init_ax5043_regs` from the values found in `AX_Radio_Lab_output/config.c` (the carrier frequency is not assigned to the FREQA register in `config.c`, but assigned to the `axradio_phy_chanfreq` variable).

When changing the carrier frequency it is further necessary to update the `freq_tbl_sin[][]` table (see below).

`void send_tone_prepare(void)`

This routine powers up the transmitter in CW mode. Further TIMER0 is set up to be clocked at $f_{\text{radio_xtal}} / 2^{\text{tone_rclk_div}}$ and to generate interrupts at $f_s = f_{\text{radio_xtal}} / 2^{\text{tone_rclk_div}} / \text{tone_t0period}$. The frequency f_s is the sampling frequency at which the AX5043 frequency register is updated.

`void send_tone(uint8_t n)`

This routine sets the frequency of the generated tone by writing the `tone_tbl`. It further resets `tone_sample_cnt`, which measures the length of the generated tone in samples. The routine returns after transmitting the tone.

`void send_tone_end()`

This routine puts the AX5043 into power-down and disables the TIMER0.

`void timer0_interrupt(void)`

This routine toggles the `FREQSEL` bit in `AX5043_PLLLOOP`, which switches between the `AX5043_FREQA` and `AX5043_FREQB` registers. It then increments the phase accumulator `tone_phase` by `tone_freq` and writes the frequency of the next sampling point to the currently unused frequency register. Further `tone_cample_cnt` is incremented. This counter measures the length of the tone in samples.

Note: The execution time of the `timer0_interrupt` ISR is roughly 10 μ s. Modifications of this routine, e.g. in order to get rid of the hard-coded carrier frequency, may increase the execution time and thus require lower f_s . (Increase `tone_rclk_div` or `tone_t0period`.)

Variables

uint8_t freq_tbl_sin[256][4]

This array contains the frequency register values sampling one period of the modulation with 256 points, thus

$$f_{\text{carrier}} + f_{\text{deviation}} \times \sin(2\pi \cdot n/256) \times \frac{2^{24}}{f_{\text{radio_xtal}}}$$

For each sampling point the 32 bit frequency register value is stored as 4 bytes in the order {FREQA0, FREQA1, FREQA2, FREQA3}. Note that the PLL requires that bit 0 of the FREQA0 is always set in order to prevent tonal behaviour of the Sigma-Delta Modulator.

Note that the full frequency is tabulated, not just the deviation from f_{carrier} . This avoids 32bit addition on each frequency update, allowing maximum sampling speed. The drawback is the lost flexibility in changing f_{carrier} .

The file MASTER/print_tab.c contains a simple routine for computing the above table on the AX8052 MCU and printing it on the DebugLink interface.

uint8_t tone_rclk_div

TIMER0 is clocked at $f_{\text{radio_xtal}} / 2^{\text{tone_rclk_div}}$

Allowed values are [0, 11].

uint16_t tone_t0period

TIMER0 interrupts for updating the frequency register are generated at the sampling frequency

$$f_s = f_{\text{radio_xtal}} / 2^{\text{tone_rclk_div}} / \text{tone_t0period}.$$

Higher f_s give higher quality representation of the tones. The default used in the example project is

$f_s = 48 \text{ MHz} / 2^{10} / 1 = 46.875 \text{ kHz}$, which is on the high side. Note: The execution time of the timer0_interrrupt ISR, which handles the frequency adjustment, is roughly 10us. Modifications of that routine, e.g. in order to get rid of the hard-coded carrier frequency, may increase the execution time and thus require lower f_s .

const uint16_t tone_tbl[]

This array lists the tone frequencies used. Default is ZVEI. The units are $(f_{\text{tone}}/f_s) * 2^{16}$, where f_s is the sampling frequency.

const uint16_t tone_len

This variable defines the tone length in samples.

Conclusion

It is possible to transmit analog FM tones as used in various selective calling schemes using the AX5043.

ON Semiconductor and  are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free
USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81-3-5817-1050

ON Semiconductor Website: www.onsemi.com

Order Literature: <http://www.onsemi.com/orderlit>

For additional information, please contact your local Sales Representative