




ARRAYJ-300XX-16P-PCB CASE 100DJ ISSUE O

DATE 31 JUL 2018







Top View

Side View

Bottom View

ArrayJ-30035-16P-PCB Pin Configuration					
J1		J2			
Pin#	Signal	Pin#	Signal		
1	S2	1	S9		
2	F1	2	F9		
3	S1	3	S10		
4	F2	4	F10		
5	S3	5	S11		
6	F3	6	F11		
7	СОМ	7	СОМ		
8	СОМ	8	СОМ		
9	F4	9	S12		
10	S4	10	F12		
11	F8	11	F16		
12	S8	12	S16		
13	СОМ	13	СОМ		
14	СОМ	14	СОМ		
15	F7	15	F15		
16	S7	16	S15		
17	F6	17	F14		
18	S6	18	S14		
19	S5	19	S13		
20	F5	20	F13		

Signal Description			
Sn	Sn SiPM n Standard Output/Anode		
Fn	SiPM n Fast Output		
COM	Common Cathode		

DOCUMENT NUMBER:	98AON95341G	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.		
DESCRIPTION:	ARRAYJ-300XX-16P-PCB		PAGE 1 OF 1	

onsemi and Onsemi are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.